



SGM4782

0.5Ω, High Speed, Low Voltage Analog Switch/Multiplexer

GENERAL DESCRIPTION

The SGM4782 is high-speed, low-voltage, low on-resistance, CMOS analog multiplexer/switch that configured as two 4-channel multiplexers. It operates from a single +1.8V to +4.2V power supply. Targeted applications include battery powered equipment that benefit from low R_{ON} (0.5Ω) and fast switching speeds ($t_{ON} = 20\text{ns}$, $t_{OFF} = 20\text{ns}$).

The SGM4782 can handle rail-to-rail analog signals and is available in Green TQFN-3x3-16L and TSSOP-16 packages.

APPLICATIONS

Communication Systems

Cell Phones

Portable Instrumentation

Audio Signal Routing

Audio and Video Switching


Computer Peripherals

Low-Voltage Data-Acquisition Systems


FEATURES

- **Voltage Operation:** 1.8V to 4.2V
- **Low On-Resistance:** 0.5Ω (TYP) at 4.2V
- **Low On-Resistance Flatness**
- **-3dB Bandwidth:** 30MHz
- **Fast Switching Times (+4.2V)**
 - t_{ON} 20ns
 - t_{OFF} 20ns
- **Low Crosstalk:** -108dB at 1MHz
- **Typical Power Consumption (< 0.01μW)**
- **TTL/CMOS Compatible**
- **Rail-to-Rail Input and Output Operation**
- **Break-Before-Make Switching**
- **Extended Industrial Temperature Range:** -40°C to +85°C
- **Available in Green TQFN-3x3-16L and TSSOP-16 Packages**

PIN CONFIGURATIONS (TOP VIEW)



TQFN-3x3-16L



TSSOP-16

FUNCTION TABLE

CONTROL INPUTS		ON SWITCHES	
Enable	Select B A	X-X0	Y-Y0
L	L L	X-X0	Y-Y0
L	L H	X-X1	Y-Y1
L	H L	X-X2	Y-Y2
L	H H	X-X3	Y-Y3
H	✓ ✓	All Switches Open	

✓ = Don't Care.



SG Micro Corp
www.sg-micro.com

REV. B. 1

SGM4782

**0.5Ω, High Speed, Low Voltage
Analog Switch/Multiplexer**

PACKAGE/ORDERING INFORMATION

MODEL	PIN-PACKAGE	SPECIFIED TEMPERATURE RANGE	ORDERING NUMBER	PACKAGE MARKING	PACKAGE OPTION
SGM4782	TQFN-3x3-16L	-40°C to +85°C	SGM4782YTQ16/TR	4782TQ	Tape and Reel, 3000
	TSSOP-16	-40°C to +85°C	SGM4782YTS/TR	SGM4782YTS	Tape and Reel, 3000

ABSOLUTE MAXIMUM RATINGS

V ₊ to GND.....	0V to 4.6V
Analog, Digital voltage range.....	-0.3V to (V ₊) + 0.3V
Continuous Current X _— , Y _— , X or Y	±250mA
Peak Current X _— , Y _— , X or Y	±400mA
Operating Temperature Range.....	-40°C to +85°C
Junction Temperature.....	150°C
Storage Temperature Range.....	-65°C to +150°C
Lead Temperature (soldering, 10s).....	260°C
ESD Susceptibility	
HBM.....	4000V
MM.....	400V

NOTE: Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

CAUTION

This integrated circuit can be damaged by ESD if you don't pay attention to ESD protection. SGMICRO recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage. ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

SGMICRO reserves the right to make any change in circuit design, specification or other related things if necessary without notice at any time. Please contact SGMICRO sales office to get the latest datasheet.

PIN DESCRIPTION

PIN		NAME	FUNCTION
TSSOP-16	TQFN-3x3-16L		
1, 5, 2, 4	15, 3, 16, 2	Y0-Y3	Analog Switch Y Inputs Y0-Y3.
3	1	Y	Analog Switch Y Output.
6	4	ENABLE	Digital Enable Input. Normally connect to GND. Drive to logic high to set all switches off.
7	5	N.C.	Not internally connected.
8	6	GND	Ground.
9	7	B	Digital Address B Input.
10	8	A	Digital Address A Input.
12, 14, 15, 11	10, 12, 13, 9	X0-X3	Analog Switch X Inputs X0-X3.
13	11	X	Analog Switch X Output.
16	14	V ₊	Positive Analog and Digital Supply Voltage Input.
—	Exposed Pad	GND	Exposed pad should be soldered to PCB board and connected to GND.



SGM4782

0.5Ω, High Speed, Low Voltage Analog Switch/Multiplexer

ELECTRICAL CHARACTERISTICS

($V_+ = +4.2V$, GND = 0V, $V_{IH} = +1.6V$, $V_{IL} = +0.6V$, $T_A = -40^\circ C$ to $+85^\circ C$. Typical values are at $V_+ = +4.2V$, $T_A = +25^\circ C$, unless otherwise noted.)

PARAMETER	SYMBOL	CONDITIONS	TEMP	MIN	TYP	MAX	UNITS
ANALOG SWITCH							
Analog Signal Range	$V_{X_}, V_{Y_}, V_X, V_Y$		-40°C to +85°C	0		V_+	V
On-Resistance	R_{ON}	$V_+ = 4.2V$, $I_{X_}, I_{Y_} = -100mA$, $V_X, V_Y = 1V$, Test Circuit 1	+25°C		0.5	0.85	Ω
			-40°C to +85°C			0.95	
On-Resistance Match Between Channels	ΔR_{ON}	$V_+ = 4.2V$, $I_{X_}, I_{Y_} = -100mA$, $V_X, V_Y = 1V$, Test Circuit 1	+25°C		0.05	0.2	Ω
			-40°C to +85°C			0.24	
On-Resistance Flatness	$R_{FLAT(ON)}$	$V_+ = 4.2V$, $I_{X_}, I_{Y_} = -100mA$, $V_X, V_Y = 1V, 2.5V$, Test Circuit 1	+25°C		0.1	0.2	Ω
			-40°C to +85°C			0.24	
Source OFF Leakage Current	I_{X_OFF} , I_{Y_OFF}	$V_+ = 4.2V$, $V_{X_}, V_{Y_} = 3.3V, 0.3V$, $V_X, V_Y = 0.3V, 3.3V$	-40°C to +85°C			1	μA
Channel ON Leakage Current	I_{X_ON} , I_{Y_ON} , $I_{X(ON)}$, $I_{Y(ON)}$	$V_+ = 4.2V$, $V_X, V_Y = 0.3V, 3.3V$, $V_{X_}, V_{Y_} = 0.3V, 3.3V$ or floating	-40°C to +85°C			1	μA
DIGITAL INPUTS							
Input High Voltage	V_{INH}		-40°C to +85°C	1.6			V
Input Low Voltage	V_{INL}		-40°C to +85°C			0.5	V
Input Leakage Current	$I_{IN_}$	$V_A, V_B = V_{ENABLE} = 0V$ or 4.2V	-40°C to +85°C			1	μA
DYNAMIC CHARACTERISTICS							
Turn-On Time	t_{ON}	$V_{IN} = 1.5V$ to 0.5V, V_X or $V_Y = 2.1V$ $R_L = 50 \Omega$, $C_L = 35pF$, Test Circuit 2	+25°C		20		ns
Turn-Off Time	t_{OFF}		+25°C		20		
Address Transition Time	t_{TRANS}	$V_{IN} = 4.2V$ to 0V, V_X or $V_Y = 2.1V$, $R_L = 50\Omega$, $C_L = 35pF$, Test Circuit 3	+25°C		30		ns
Break-Before-Make Time Delay	t_D	$V_{IN} = 4.2V$ to 0V, V_X or $V_Y = 2.1V$, $R_L = 50\Omega$, $C_L = 35pF$, Test Circuit 4	+25°C		20		ns
Charge Injection	Q	$C_L = 1nF$, Test Circuit 5	+25°C		-18		pC
Off Isolation	O_{ISO}	Signal = 0dBm, $V_{BIAS} = 2.1V$, $R_L = 50\Omega$, $C_L = 35pF$, Test Circuit 6	100kHz	+25°C		-75	dB
			1MHz	+25°C		-55	
Channel-to-Channel Crosstalk	X_{TALK}	Signal = 0dBm, $V_{BIAS} = 2.1V$, $R_L = 50\Omega$, $C_L = 35pF$, Test Circuit 6	100kHz	+25°C		-106	dB
			1MHz	+25°C		-108	
-3dB Bandwidth	BW	Signal = 0dBm, $V_{BIAS} = 2.1V$, $R_L = 50 \Omega$, Test Circuit 6	+25°C		30		MHz
Channel ON Capacitance	C_{X_ON} , C_{Y_ON} , $C_{X(ON)}$, $C_{Y(ON)}$		+25°C		146		pF
POWER REQUIREMENTS							
Power Supply Range	V_+		-40°C to +85°C	1.8		4.2	V
Power Supply Current	I_+	$V_+ = 4.2V$, $V_A, V_B, V_{ENABLE} = 4.2V$ or 0V	-40°C to +85°C			1	μA

SGM4782
**0.5Ω, High Speed, Low Voltage
Analog Switch/Multiplexer**
ELECTRICAL CHARACTERISTICS





($V_+ = +2.7V$ to $+3.6V$, GND = 0 V, $V_{IH} = +1.6V$, $V_{IL} = +0.4V$, $T_A = -40^\circ C$ to $+85^\circ C$. Typical values are at $V_+ = +3.0V$, $T_A = +25^\circ C$, unless otherwise noted.)

PARAMETER	SYMBOL	CONDITIONS	TEMP	MIN	TYP	MAX	UNITS
ANALOG SWITCH							
Analog Signal Range	$V_{X_}, V_{Y_}, V_X, V_Y$		-40°C to +85°C	0		V_+	V
On-Resistance	R_{ON}	$V_+ = 2.7V$, $I_{X_}, I_{Y_} = -100mA$, $V_X, V_Y = 1V$, Test Circuit 1	+25°C		0.6	0.95	Ω
			-40°C to +85°C			1.05	
On-Resistance Match Between Channels	ΔR_{ON}	$V_+ = 2.7V$, $I_{X_}, I_{Y_} = -100mA$, $V_X, V_Y = 1V$, Test Circuit 1	+25°C		0.05	0.2	Ω
			-40°C to +85°C			0.24	
On-Resistance Flatness	$R_{FLAT(ON)}$	$V_+ = 2.7V$, $I_{X_}, I_{Y_} = -100mA$, $V_X, V_Y = 1V, 2.5V$, Test Circuit 1	+25°C		0.1	0.2	Ω
			-40°C to +85°C			0.24	
Source OFF Leakage Current	I_{X_OFF}, I_{Y_OFF}	$V_+ = 3.6V$, $V_{X_}, V_{Y_} = 3.3V, 0.3V$, $V_X, V_Y = 0.3V, 3.3V$	-40°C to +85°C			1	μA
Channel ON Leakage Current	$I_{X_ON}, I_{Y_ON}, I_{X(ON)}, I_{Y(ON)}$	$V_+ = 3.6V$, $V_X, V_Y = 0.3V, 3.3V$, $V_{X_}, V_{Y_} = 0.3V, 3.3V$ or floating	-40°C to +85°C			1	μA
DIGITAL INPUTS							
Input High Voltage	V_{INH}		-40°C to +85°C	1.5			V
Input Low Voltage	V_{INL}		-40°C to +85°C			0.4	V
Input Leakage Current	$I_{IN_}$	$V_A, V_B = V_{ENABLE} = 0V$ or $2.7V$	-40°C to +85°C			1	μA
DYNAMIC CHARACTERISTICS							
Turn-On Time	t_{ON}	$V_{IN} = 1.5V$ to $0.5V$, V_X or $V_Y = 1.5V$, $R_L = 50\Omega$, $C_L = 35pF$, Test Circuit 2	+25°C		33		ns
Turn-Off Time	t_{OFF}		+25°C		20		
Address Transition Time	t_{TRANS}	$V_{IN} = 1.5V$ to $0V$, V_X or $V_Y = 1.5V$, $R_L = 50 \Omega$, $C_L = 35pF$, Test Circuit 3	+25°C		36		ns
Break-Before-Make Time Delay	t_D	$V_{IN} = 1.5V$ to $0V$, V_X or $V_Y = 1.5V$, $R_L = 50\Omega$, $C_L = 35pF$, Test Circuit 4	+25°C		18		ns
Charge Injection	Q	$C_L = 1nF$, Test Circuit 5	+25°C		-18		pC
Off Isolation	O_{ISO}	Signal = $0dBm$, $V_{BIAS} = 1.5V$, $R_L = 50\Omega$, $C_L = 35pF$, Test Circuit 6	100kHz	+25°C		-75	dB
			1MHz	+25°C		-55	
Channel-to-Channel Crosstalk	X_{TALK}	Signal = $0dBm$, $V_{BIAS} = 1.5V$, $R_L = 50\Omega$, $C_L = 35pF$, Test Circuit 6	100kHz	+25°C		-106	dB
			1MHz	+25°C		-108	
-3dB Bandwidth	BW	Signal = $0dBm$, $V_{BIAS} = 1.5V$, $R_L = 50\Omega$, Test Circuit 6	+25°C		30		MHz
Channel ON Capacitance	$C_{X_ON}, C_{Y_ON}, C_{X(ON)}, C_{Y(ON)}$		+25°C		146		pF


SGM4782

**0.5Ω, High Speed, Low Voltage
Analog Switch/Multiplexer**



TYPICAL PERFORMANCE CHARACTERISTICS






TEST CIRCUITS



Test Circuit 1. On Resistance

Test Circuit 2. Enable Switching Times (t_{OFF} , t_{ON})Test Circuit 3. Address Transition Times (t_{TRANS})

TEST CIRCUITS (Cont.)

Test Circuit 4. Break-Before-Make Interval (t_D)Test Circuit 5. Charge Injection (Q)


Test Circuit 6. -3dB Bandwidth, Off-Isolation and Crosstalk

SGM4782


**0.5Ω, High Speed, Low Voltage
Analog Switch/Multiplexer**

PACKAGE OUTLINE DIMENSIONS


TQFN-3x3-16L




TOP VIEW



BOTTOM VIEW



SIDE VIEW



RECOMMENDED LAND PATTERN (Unit: mm)



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	MIN	MAX	MIN	MAX
A	0.700	0.800	0.028	0.031
A1	0.000	0.050	0.000	0.002
A2	0.203 REF		0.008 REF	
D	2.900	3.100	0.114	0.122
D1	1.600	1.800	0.063	0.071
E	2.900	3.100	0.114	0.122
E1	1.600	1.800	0.063	0.071
k	0.200 MIN		0.008 MIN	
b	0.180	0.300	0.007	0.012
e	0.500 TYP		0.020 TYP	
L	0.300	0.500	0.012	0.020

SGM4782

**0.5Ω, High Speed, Low Voltage
Analog Switch/Multiplexer**

PACKAGE OUTLINE DIMENSIONS

TSSOP-16




Symbol	Dimensions In Millimeters		Dimensions In Inches	
	MIN	MAX	MIN	MAX
A		1.100		0.043
A1	0.050	0.150	0.002	0.006
A2	0.800	1.000	0.031	0.039
b	0.190	0.300	0.007	0.012
c	0.090	0.200	0.004	0.008
D	4.900	5.100	0.193	0.201
E	4.300	4.500	0.169	0.177
E1	6.250	6.550	0.246	0.258
e	0.650 BSC		0.026 BSC	
L	0.500	0.700	0.02	0.028
H	0.25 TYP		0.01 TYP	
θ	1°	7°	1°	7°


SGM4782**0.5Ω, High Speed, Low Voltage
Analog Switch/Multiplexer**

TAPE AND REEL INFORMATION

REEL DIMENSIONS




TAPE DIMENSIONS



NOTE: The picture is only for reference. Please make the object as the standard.

KEY PARAMETER LIST OF TAPE AND REEL

Package Type	Reel Diameter	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P0 (mm)	P1 (mm)	P2 (mm)	W (mm)	Pin1 Quadrant
TQFN-3x3-16L	13"	12.40	3.35	3.35	1.13	4.00	4.00	2.00	12.00	Q1
TSSOP-16	13"	12.4	6.9	5.6	1.2	4.0	8.0	2.0	12.0	Q1

CARTON BOX DIMENSIONS

NOTE: The picture is only for reference. Please make the object as the standard.

KEY PARAMETER LIST OF CARTON BOX

Reel Type	Length (mm)	Width (mm)	Height (mm)	Pizza/Carton
13"	386	280	370	5